



Technical specifications

Features

Mesh WiFi Repeater for the highest performance requirements

Can also be connected to a router via network cable (LAN bridge)

Encryption with WPA2 (802.11i), additional

With Mesh WiFi you can combine several wireless access points into one intelligent system (FRITZ!OS 6.90 and later) Find out more at en.avm.de/mesh

Three wireless radio units: 1,733 Mbit/s + 866 Mbit/s (5 GHz) + 400 Mbit/s (2.4 GHz) for the optimal supply of multiple wireless devices

Two gigabit LAN ports: Connected devices (computers, printers, audio/video players, etc.) are granted WiFi functionality

WPA3 transition mode (in LAN bridge mode)

Compatible with all common wireless routers

Simple, secure configuration at the touch of a button (WPS method)

Display shows connection quality and status

Supports the IPv6 internet protocol

Easy to install

Optimized for use with all FRITZ!Box models

Simple installation at the touch of a button using Wi-Fi Protected Setup (WPS)

Easy operation via browser-based user interface (<http://fritz.repeater>)

Ports and

Connection to mains with power adapter

2 x gigabit ports (10/100/1000 Mbit/s)

interfaces

provided (230 V, 50 Hz)

Wireless access point:
802.11ac (1,733
Mbit/s), 802.11n (400
Mbit/s)

Wireless LAN: 2 x
5 GHz, 2.4 GHz

Package contents

FRITZ!Repeater 3000

Quick guide

Power adapter

Network cable

Device properties

Measurements (W x H x
D): approx. 8.8 x 18.4 x
13.6 cm

Total power
consumption:
maximum 11.4 watts,
average 6 watts

Warranty

5-year
manufacturer's warranty
for end customers, as
per the warranty
conditions

Article number

20002888

FRITZ! – Here's why!

Enjoy the benefits of FRITZ!
products and services

Service

We're to help with knowledge
documents, downloads, videos
and more